

LED Stage Lighting Operating Manual

240W 18 LED PAR Light

USER MANUAL

Thank you so much for choosing this product. It adopts the most advanced lamps. It conquers a lot of disadvantages such as power wasting, short using life, high temperature, etc. It has advantages of power saving, long life (which can reach 60,000 hours in general circs), high brightness, clear colors. It is the best stage illuminating and various effect decorative products

DMX 512 Control: 8 Channel Mode (A001)

CH	Function	Instruction
CH 1	Dimmer	RGBW main dimmer, from darker to brighter
CH 2	R dimmer	R dimmer, from darker to brighter
CH 3	G dimmer	G dimmer, from darker to brighter
CH 4	B dimmer	B dimmer, from darker to brighter
CH 5	W dimmer	W dimmer, from darker to brighter
CH 6	Strobe	R, G, B, W strobe, from slower to faster
CH 7	Function Choices	0-50: 8CH DMX Control Auto Modes: 51-100: Different Colors Output 101-150: Colors Jump Change 151-200: Colors Gradate. 201-250: Colors Pulse Change. 251-255: Sound Active
CH 8	Function Speed	Speed function, from slower to faster

DMX 512 Control: 4 Channel Mode (d001)

CH	Function	Instruction
CH 1	R Dimmer	Dimmer. Darker to brighter
CH 2	G Dimmer	Dimmer. Darker to brighter
CH 3	B Dimmer	Dimmer. Darker to brighter
CH 4	W Dimmer	Dimmer. Darker to brighter

Functions:

No	Display	Function	Instruction
1	A001	DMX Address (001~512)	DMX-512 address set 8 Channels mode
2	d001	DMX Address (001~512)	DMX-512 address set 4 Channels mode
3	r255	Red (0~255)	Change the brightness
4	G255	Green (0~255)	Change the brightness
5	b255	Blue (0~255)	Change the brightness
6	u255	White (0~255)	Change the brightness
7	Fh99	Strobe/Flash (01~99)	Change the speed
8	Cl01	Different Color (01~08)	Change the brightness
9	Cc99	Jump Change (01~99)	Change the speed
10	De99	Gradate Change (01~99)	Change the speed
11	Cp99	Pulse Change (01~99)	Change the speed
12	SU01	Sound Active (01~99)	Change the sensitivity

Specifications:

Brand: U`King

Model: ZQ-B35

Energy Consumption: 240W

Voltage: 100 - 240V AC 50 / 60Hz, 180W

Shell Material: cast aluminum

Shell Color: black

Lamp Bead type: LED

Lamp Beads: 18 * 15W 4 in 1

Light Bead Effect: 4 in 1 LED lamp beads

Beam Angle: 45 °

Control Mode: Auto, Sound Active, DMX 512, Master&Slave

Use Channels: 8 channels

Color Dimming: Red/Green/Blue/White, dims independently

Sound Control: Sensitivity adjustable

Life Time: 50,000h

Operating Temperature: -25 °C to +35 °C

Cooling: Air cooled

Suitable for: Disco, nightclub, party ...